

25 Jul 67

DATA FOR THE MODEL 1 AND MODEL 2 INCINERATORS

		Model 1		Model 2	
<u>Motor,</u>	hp	7-1/2		2	
	Phase	three		three	
	Voltage	208, 220/440		208, 220/440	
	Frame No.	215		184	
	Shaft, dia, in	1-1/8		7/8	
	Shaft length, in.	std.		3-1/2	
	Present G.E. Mod.	5K215 AG1		5K184 AG1897	
	Type	K		K	
	Code	G		K	
	Frequency, cycles	60	50	60	50
	Speed, rpm	3500	2900	3500	2915
	Full load current				
	lower voltage, amp.	20	20+	5.6	6.2
	higher voltage, amps	10	10+	2.8	3.1
	Temperature rise, C	40	60	40	50
	Service factor	1.2	1.0	1.2	1.0

Magnetic Starter		Three phase		Three phase		Single phase	
Allen-Bradley, Bulletin No.		709		709		709 SP	
Size No.		1		0		1	
Form No.		1		1		1	
Type No.		1		1		1	
Frequency, cycles		60 or 50		60 or 50		60 or 50	
Allen-Bradley holding coils							
Frequency, cycles		60		60		60	
110 volts, Coil No.		1L06		1L06		1L257	
220 volts, Coil No.		1L07		1L07		1L289	
440 volts, Coil No.		1L11		1L11		1L289	

Allen-Bradley heater elements		60 or 50		60 or 50		60 or 50	
Frequency, cycles		60 or 50		60 or 50		60 or 50	
110 volts, Heater No.		N-39		N-25		N-31	
220 volts, Heater No.		N-31		N-18		N-31	
440 volts, Heater No.		N-31		N-18		N-31	

* Coils No. 1L257 and 1L289 are dual voltage coils with three wire leads. All other coils are single voltage with two wire a different